Product data sheet



EST-M04

Microphone Station (4 buttons)

Overview

The EST-M04 is a 4 button analog microphone with built in gong, push to talk and bi-color LED indicating the ready-to-speak status.

To operate the device first select the Zones by pressing designated buttons and then press MIC ON button, the status LED will switch from red (not ready for broadcast) to steady green light. In the event of an active built in gong, the status LED will turn green once the gong has ended. When finished transmitting the message release the MIC ON button to deactivate the gooseneck mic.



Details

- Solid construction
- Zone configuration buttons at front panel with LED
- Microphone on/off button with LED
- Flexible microphone neck
- Microphone volume control at rear panel
- Gong feature at rear panel with volume

EST-M04

Microphone Station (4 buttons)

Technical specifications

Eléctrico	
Voltaje de	20-57 VDC
funcionamiento	
Físico	
Peso neto	1.2 kg
Estándares y regulaciones	
Normativas	EN54-16
Electrical	
Efficiency	10 mV / Pa
Output level	775 mV
Physical	
Maximum distance from	250 m
amplifier	
Recommended cable	UTP
type	
Connector Type	8P8C (RJ45)

As a company of innovation, UTC Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit UTC Fire & Security online or contact your sales representative.

